



PRODUCT DETAILS

The Power+ Parallel Box is a passive parallel connection box that allows two W&C inverter generators, two W&C portable power stations, or one of each, to operate together in parallel and supply a single, larger combined power output through the two 32A outlets.

OPERATION

The Power+ Parallel Box itself contains no control electronics. Parallel load-sharing and synchronisation are managed by the inverter and battery management systems built into the connected W&C products. It is this inbuilt intelligence that allows W&C products of different sizes and types to be paired together - something conventional parallel kits, which require two identical generators, cannot do.

COMPATIBILITY

ANY TWO LISTED PRODUCTS: SAME MODEL, DIFFERENT SIZES, OR HYBRID (POWER STATION + GENERATOR)

PORTABLE POWER STATIONS

2 x WC-BG2000, or 2 x WC-BG3600, or 2 x WC-BG5500

PETROL INVERTER GENERATORS

2 x WC-P3200SI, or 2 x WC-P6000SI, or 2 x WC-P9000SI, or 2 x WC-P11250I

TECHNICAL DATA

RATED VOLTAGE	240V AC - Max Load 2 x 32 amp
MAX COMBINED THROUGHPUT	Limited to approx. 90% of the combined RATED output of the connected products
DIMENSIONS	300 wide x 185 high x 140 deep (Excluding cable and glands)
NET WEIGHT	Nominal 2.6kg

